

Janam XP30 - Nokia 6126 Cellular Phone WWAN Data Service Setup

Access the Internet with Janam's XP30 Palm PDA over a Wireless Wide Area Network

Go mobile with Janam's XP30. Don't be confined to WiFi hotspots and cabled modems. Check e-mail and access the Internet anywhere you have cellular phone coverage with a Nokia 6126 Bluetooth-enabled cellular phone and Janam's XP30, without any cables tying you down.

MINIMUM REQUIREMENTS:

- Nokia 6126 handset purchased through AT&T
- Janam XP30 (Part Number XP30W-1NCLB00)
- Media Max Cingular Data Service with CCI Update*

*This update can be requested by calling Cingular Technical Support.



SETUP PROCEDURE:

1

Setting up the Nokia handset

- (A) On the Nokia handset, tap "Menu".
- (B) Scroll to Settings and tap "Select".
- (C) Scroll to Connectivity and tap "Select".
- (D) Scroll to Bluetooth and tap "Select".
- (E) Scroll to Bluetooth again and tap "Select".
- (F) Scroll to On and tap "Select".
- (G) Scroll to My phone's visibility and press "Select".
- (H) Scroll to Temporary visibility and tap "Select" to open a Bluetooth connection.

A small timer will appear under the tab "Temporarily visible". Under temporary visibility, the Nokia handset will remain discoverable for only two minutes. The connection to the Janam device must be made within this time frame.

(See Step 2 on next page).

Janam XP30 - Nokia 6126 Cellular Phone WWAN Data Service Setup

2

Setting up the connection

- (A) On the XP30, tap the "Home" icon in the Graffiti Writing area. Tap "Prefs" then tap "Bluetooth".
- (B) From the Bluetooth drop down menu, tap "Enabled".
- (C) From the Discoverable drop down menu, tap "No".
- (D) Tap "Trusted Devices" then tap "Add Device".
- (E) Tap to select the handset and tap "OK". Type a Passkey (example: "1234") and tap "OK".
- (F) On the handset, a "Pair with the PC?" prompt will appear. Tap "Accept". Type the same pass code (passkey) as above and tap "OK".
- (G) Tap "Yes" to the "Allow this device to connect automatically?" message. Tap "Done".
- (H) Return to the Preferences menu and tap "Connection" then tap "New".
- (I) In the Name field, type "ATT Data".
- (J) In the drop down menu named Via, tap to select "Bluetooth".
- (K) In the Device field, tap on "Tap to Find" to select the handset.
- (L) Tap to select the device from the list and tap "OK".
- (M) Tap to select PC from the Connect to drop down menu. Tap "OK".
- (N) Return to the Preferences menu and tap on "Network". Tap the Blue Preferences tag (upper left corner) and tap "New".
- (O) In the Service field, type "ATT Data". In the User name field, type "ISP@CINGULARGPRS.COM".
- (P) In the Password field, tap on "-Prompt-". Type "CINGULAR1" and tap "OK".
- (Q) From the Connection drop down menu, tap to select ATT Data then tap "Details".
- (R) Ensure "PPP" is selected as the Connection Type. Check the boxes to Query DNS and obtain IP Address as Automatic. Tap on the Script button.
- (S) Tap on the arrow next to End, and tap to select "Send", and type: "at+cgdcont=1,"IP","isp.cingular"
- (T) Tap on the arrow next to End, and tap to select "Send CR".
- (U) Tap on the arrow next to End, and tap to select "Send", and type "atdt*99#". Tap on the arrow next to End, and tap to select "Send CR".
- (V) Tap on the arrow next to End, and tap to select "Wait For", then type "CONNECT".
- (W) Tap "OK" then tap "OK" again.

3

Establishing the connection

- (A) On the XP30, return to Network from the Preferences window.
- (B) Tap "Connect".

You will now be connected to the AT&T data service.